

QUICK OPERATING INSTRUCTIONS



PASSWORD: 4 last digit of the serial numberer (back of the device)



POWER ON

Press the power button till you hear a long 'biip' (the operating system is starting and is busy for a while. Be patient) As from the moment you get **READ CARD** is the device ready for use.

POWER OFF

Press the same button till you get **POWER OFF** on the screen.



CHARGING

With a full battery, you will be able to handle approximatively 400 transactions. We advise to charge the device daily. At full charge, the red led light beside the power plug switches to green.



TO PAY

When the **READ CARD** is on the screen, the customer inserts his payment card. Take then the device back en fill in the amount (do it in eurocent). Now press **ENTER**. Give the device to the customer so he can fill in his **PIN** code and press **ENTER**. A ticket will be printed for your own administration.

"PRINT COPY" customer YES = **ENTER** NO = **CLEAR**



VIA NFC ?

Easy. Input immediately the amount in eurocent en give the device to the customer. The customer have to present his payment card one second (not less) just above the screen and the payment will be confirmed.



TO CANCEL THE LAST PAYMENT

Press **FUNC** and select **▲ ▼ CANCEL PAYMENT** and press **ENTER**. Fill in the password and press again **ENTER**. You get **READ CARD** and the customer inserts his card in the front opening of the device. Input the same amount that was previously paid and press **ENTER**. Input the "**AUT. CODE**" (last ticket: you'll find it right under the date) and press **ENTER**. "PRINT COPY" for the customer YES = **ENTER** NO = **CLEAR**



COPY OF THE LAST TRANSACTION

Press **FUNC** and select **▲ ▼ REPRINT TICKET** and press **ENTER**



GET THE DAILY TOTAL

Press **MENU** and **2_{ABC} ADMINISTRATION** and fill in the password; press **ENTER**. Press **6_{MNO} PRINT TRANS LOG** and select "**TOTALS + CARDS**". Fill in date/time of the beginning and end of the period you want a report; press **ENTER**. That's it! The transactions log will be printed.